

SUBSTRATE PROCESSING SYSTEM AND SUBSTRATE PROCESSING METHOD

BACKGROUND OF THE INVENTION

The present invention relates to a substrate processing
5 system and a substrate processing method for performing a
series of processes to several types of substrates such as
semiconductor wafers and glass substrates used for liquid
crystal displays.

Micro circuit patterns are formed by photolithography
10 in fabrication of glass substrates used for liquid crystal
displays (LCD substrates) and semiconductor devices, etc.

A circuit pattern is formed in photolithography by
applying a resist on a substrate such as an LCD substrate
and a semiconductor wafer and forming the resist film followed
15 by exposure to the pattern, development and etching.

Photolithographic systems for handling several wafers
have been developed in recent trend of large diameter for
semiconductor wafers. A complex processing system capable
of resist-application and development, for example, takes
20 out wafers one by one from a cassette into a processing unit
in which the wafers are processed one by one, and the processed
wafers are returned to the cassette one by one.

A processing time for each of several units in this
complex processing system is called one cycle. The system
25 cannot proceed to the next processes until the previous
processes are completed in every unit for one cycle.

Therefore, in a complex processing system that
transfers a wafer to the next processing unit after the
previous process has been completed, a process to be performed
30 by the present unit is susceptible to the process performed
by the previous unit, or the present unit has to wait for
the completion of the previous processing (called
waiting-time consumption).

In a series of processing, such as, baking, cleaning
35 and development performed in this order, the developing
process requires a relatively long processing time. Due to
long developing process time, a wafer for which the baking

and cleaning processes have been completed has to remain in the baking or the cleaning unit to wait for completion of the developing process to the previous wafer. A wafer will be over-baked when it remains in the baking unit for such
 5 a long time.

A thermal processing time is precisely controlled in wafer processing recently. Such over-baking for a period longer than a controlled time, however, varies pattern width formed through a resist. Desired patterns thus cannot be
 10 formed.

SUMMARY OF THE INVENTION

In order to solve the problem discussed above, a purpose of the present invention is to provide a substrate processing
 15 apparatus that reduces effects of waiting time unnecessarily consumed (rate controlling) by any processing unit.

The present invention provides a substrate processing system including first to n-th processing units ($n = 1, 2, \dots, N$) each having at least one identical unit for performing
 20 first to n-th wafer-processing for given periods t_1 to t_n , respectively, the processing being performed in order from the first unit to the n-th unit, a plurality of substrates being simultaneously processed by different types of the processing units for one cycle, the system including: a
 25 loading/unloading section for taking in and out the substrates; a first transfer section for receiving/transferring the substrates from/to the loading/unloading section and transferring the substrates one by one to each processing unit; and a controller for controlling the first
 30 transfer section and the processing units so that each processing unit processes the substrates one by one in accordance with one-cycle time as a standard time, the one-cycle time being the maximum period among periods t_1/m to t_n/m obtained by dividing the periods t_1 to t_n by the number
 35 "m" of the identical units of the first to n-th processing units.

In this substrate processing system according to the

present invention, the controller may control the first transfer section and the processing units so that the processing time required for each processing unit corresponds to the one-cycle time. The processing time required for each
 5 processing unit may include a pre-transfer time, a net processing time, a post-transfer time and a plurality of waiting times. The waiting times may be allocated before or after one of the pre-transfer time, the net processing time and the post-transfer time in the processing time required
 10 for each processing unit.

In this substrate processing system according to the present invention, the controller may control the first transfer section and the processing units so that the processing time required for each processing unit corresponds
 15 to division of the one-cycle time by an integer. The processing time required for each processing unit may include at least a pre-transfer time, a net processing time and a post-transfer time. The processing time required for a desired processing unit may further include a waiting time.

In this substrate processing system according to the present invention, the controller may control the first transfer section and the processing units so that the total of the processing times for the successive "n" number of processing units equals to one-cycle time \times n. The
 25 processing time required for each processing unit may include at least a pre-transfer time, a net processing time and a post-transfer time. The processing time required for a desired processing unit may further include a waiting time.

In this substrate processing system according to the present invention, the processing units may include at least one thermal processing unit. The thermal processing unit may have a heating mechanism and a lift-up mechanism for holding each substrate so that the substrate is distant from the heating mechanism, the thermal processing unit waiting for
 35 thermal processing while the lift-up mechanism is holding the substrate as distant from the heating mechanism.

In this substrate processing system according to the

present invention, the processing units may include at least one developing unit for developing a resist applied onto each substrate.

5 In this substrate processing system according to the present invention, the processing units may include at least one exposing apparatus for exposing a resist applied onto each substrate.

10 This substrate processing system according to the present invention may further include a second transfer section provided as accessible to each of the processing units for transferring each substrate from one of the processing units to another.

Moreover, the present invention provides a substrate-processing system including first to n-th processing units
 15 (n = 1, 2, ..., N) each having at least one identical unit for performing first to n-th wafer-processing for given periods t1 to tn, respectively, the processing being performed in order from the first unit to the n-th unit, a plurality of substrates being simultaneously processed by different type
 20 of the processing units for one cycle, the system including: a loading/unloading section for taking in and out the substrates; a first transfer section for receiving/transferring the substrates from/to the loading/unloading section and transferring the substrates one by one to each
 25 processing unit; a second transfer section for receiving/transferring the substrates from/to the processing units; and a controller for controlling the first transfer section, the second transfer section and the processing units, when the substrates are simultaneously processed by the
 30 different types of processing units, so that each processing unit processes the substrates one by one within one-cycle time that corresponds at least to either a first total transfer time or a second total transfer time that is larger than the other, the first total transfer time being the total of
 35 periods in the one cycle for the first transfer section required for receiving/transferring each substrate from/to the loading/unloading section and transferring the substrate

to each processing unit, the second total transfer time being the total of periods in the one cycle for the second transfer section required for receiving/transferring the substrate from/to the processing units.

5 In this substrate processing system according to the present invention, the controller may calculate the maximum period among periods $t1/m$ to tn/m obtained by dividing the periods $t1$ to tn by the number "m" of the identical units of the first to n-th processing units and sets the maximum
10 among the maximum period, the first total transfer time and the second transfer time as the one-cycle time for controlling the first and the second transfer sections.

In this substrate processing system according to the present invention, at least one of the processing units may
15 be a substrate-receiving unit for receiving and processing each substrate, the controller calculating the total receiving and processing period for the substrate-receiving unit for receiving and processing each substrate and setting the maximum among the total receiving and processing period,
20 the first total transfer time and the second transfer time as the one-cycle time.

This substrate processing system according to the present invention may further include: an exposing apparatus;
and a third transfer section for receiving the substrates
25 from the processing units and transferring the substrates to the exposing apparatus, wherein the controller sets the maximum among the first total transfer time, the second total transfer time and a third total transfer time for the third transfer section required for the one cycle as the one-cycle
30 time.

Moreover, the present invention provides a method of processing substrates with first to n-th processing units ($n = 1, 2, \dots, N$) each having at least one identical unit for performing first to n-th wafer-processing for given periods
35 $t1$ to tn , respectively, the processing being performed in order from the first unit to the n-th unit, a plurality of substrates being simultaneously processed by different types

of the processing units for one cycle, the method including the steps of: processing the substrates one by one in accordance with one-cycle time as a standard time, the one-cycle time being the maximum period among periods $t1/m$ to tn/m obtained by dividing the periods $t1$ to tn by the number "m" of the identical units of the first to n-th processing units; and performing processing to each substrate in at least one of the processing units with a waiting time.

10

BRIEF DESCRIPTION OF DRAWINGS

FIG. 1 is a plan view showing the whole structure of a first embodiment of a substrate processing system according to the present invention;

15 FIG. 2 is a front view showing the substrate processing system;

FIG. 3 is a rear view showing the substrate processing system;

FIG. 4 is a schematic view showing processing units that constitute the substrate processing system;

20 FIG. 5 shows a control block diagram of the substrate processing system;

FIG. 6 shows a flow chart for the substrate processing system;

FIG. 7 illustrates data entry to the main panel;

25 FIGS. 8A and 8B show vertical sections of the substrate processing system;

FIG. 9 is a timing chart for substrate processing in a transitional state;

30 FIG. 10 is a timing chart for substrate processing in a steady state;

FIG. 11 is a timing chart for a second embodiment of a substrate processing system according to the present invention in a steady state;

35 FIG. 12 is a timing chart for a third embodiment of a substrate processing system according to the present invention in a steady state; and

FIG. 13 is a plan view showing the whole structure of

a modification to a substrate processing system according to the present invention.

DETAILED DESCRIPTION OF PREFERRED EMBODIMENTS

Preferred embodiments according to the present invention will be disclosed with reference to the attached drawings.

First Embodiment

FIGS. 1 to 5 illustrate a substrate processing system 1 according to the present invention. FIGS. 1, 2 and 3 are a plan view, a front view and a rear view, respectively, showing the whole structure of the substrate processing system 1 without an exposing apparatus 12.

As shown in FIG. 1, the substrate processing system 1 is equipped with a loading/unloading section 2 that takes out wafers W as substrates one by one from cassettes CR that contains several wafers, a processing section 3 having several processing units for performing processes such as resist application and development to each wafer W taken out by the loading/unloading section 2, and an interface section 4 for transferring each resist-applied wafer W to the exposing apparatus 12 as a processing section.

The interface section 4 has a second sub-arm mechanism 10 by which each wafer W is transferred to the exposing apparatus 12. The loading/unloading section 2 has a table 5 on which the cassettes CR are loaded and unloaded while each contains for example 25 semiconductor wafers at a time.

As shown in FIG. 1, several cassettes CR for example four are aligned at positioning protrusions 5a on the table 5 in an X-direction while a wafer inlet/outlet of each cassette CR faces the processing section 3.

A first sub-arm mechanism 6 is a first transfer means that is movable in the cassette-alignment direction (X-direction) and a wafer-alignment direction (Z-direction) for the wafers W contained in the cassettes CR for selective access to each cassette CR.

Moreover, the first sub-arm mechanism 6 is rotatable

in a θ -direction so that it transfers each wafer W to a main-arm mechanism 7 as a second transfer means provided in the processing section 3. The mechanism 6 is also accessible to an alignment unit ALIM and an extension unit EXT belonging to a multi-stage section of a third processing-unit group G3 of the processing section 3, as disclosed below.

The wafers W are transferred from the loading/unloading section 2 to the processing section 3 via the third processing-unit group G3. The unit group G3 consists of several processing units stacked as shown in FIG. 3.

In detail, the third processing-unit group G3 consists of a cooling unit COL for cooling the wafers W, an adhesion unit AD for hydrophobic processing for enhanced resist fixability to the wafers W, the alignment unit ALIM for wafer positioning, the extension unit EXT for setting the wafers W in a waiting mode, two pre-baking units PREBAKE for thermal processing before exposure, a post-baking unit POBAKE for thermal processing after development and a post-exposure baking unit PREBAKE for thermal processing after exposure, stacked in this order from the bottom to up.

The wafers W are transferred to the main-arm mechanism 7 via the extension unit EXT and the alignment unit ALIM. As shown in FIG. 1, the main-arm mechanism 7 is surrounded by a first to a fifth processing-unit group G1 to G5 including the third processing-unit group G3. Like the third group G3, each of the unit groups G1, G2, G4 and G5 consists of several stacked processing units.

The main-arm mechanism 7 has a main arm 8, as shown in FIG. 3, that can be elevated in a Z-direction inside a tubular guide 9 extending in a vertical direction. The tubular guide 9 is connected to a rotary shaft of a motor (not shown) so that it rotates with the main arm 8 about the rotary shaft, thus the main arm 8 being rotatable in the θ -direction. Instead, the tubular guide 9 may be connected to another rotary shaft (not shown) rotated by the motor.

As disclosed, the main arm 8 is driven in the vertical direction so that the wafers W can be transferred to any unit

in the processing-unit groups G1 to G5.

The fourth processing-unit group G4 consists of, as shown in FIG. 3, two cooling units COL, an extension unit EXT, another cooling unit COL, two pre-baking units PREBAKE and two post-baking unit POBAKE, stacked in this order from the bottom to up.

The fifth processing-unit group G5 is provided optionally. It is structured like the fourth processing-unit group G4 in this embodiment. The fifth unit group G5 is movable along rails 11, as shown in FIG. 13, for easy maintenance of the main-arm mechanism 7 and the first to the fourth processing-unit groups G1 to G4.

The present invention achieves drastic reduction in space for system installation when applied to the substrate processing system shown in FIGS. 1 to 3 because of the stacked structure of the processing units.

FIG. 4 is a schematic view showing the processing units for each unit group installed in the substrate processing system. Several units are provided for those requiring a long processing time such as pre-baking units PREBAKE and resist-developing apparatus DEV, as shown in FIG. 4.

Provision of a plurality of identical units each requiring a relatively long processing time reduces unnecessary waiting-time consumption (rate controlling) which may otherwise occur to the entire system. For the same reason, a plurality of identical units such as the cooling units COL are provided for several processes. The identical units are discriminated therebetween with numerals attached to their names such as COT1 and COT2.

FIG. 5 shows a control block diagram of the substrate processing system 1. The loading/unloading section 2 has a main panel 2a, on the outer wall at the front side, for total-system control and operations such as recipe settings, wafer-flow registration and alarm processing. The main panel 2a is a touch-censer type via which an operator touches a screen with a touch pen for system operation.

The main panel 2a is connected to a controller 13 so

that data on recipe, etc., entered via the touch panel 2a are fed to the controller 13. Based on the data, the controller 13 sends several types of commands to and controls the first and the second transfer mechanisms 6 and 7, the loading/unloading section 2, the processing section 3, the interface section 4 and exposing apparatus 12. The controller 13 is shown outside the system 1 in FIG. 5. It will, however, be installed, for instance, in the loading/unloading section 2 in actual use.

Monitor display changes when an operator touches the main panel 2a at particular display sections for detailed process settings for the processing units such as temperature, net processing time and rotation speed for resist applying apparatus.

Disclosed next is a substrate-processing procedure for the substrate processing system 1 described above with reference to FIG. 6.

Performed first before substrate processing are recipe settings via the main panel 2a provided on the front side of the substrate processing system 1 shown in FIGS. 1 to 3.

A transfer recipe is set first in the recipe settings. The transfer recipe includes contents of processing to be performed such as adhesion, development and exposure and their order. The number of wafers W to be processed may also be set in the recipe settings. The recipe settings are performed by touching the main panel 2a provided on the loading/unloading section 2 with a touch pen.

In detail, steps and processing units such as shown in FIG. 7 are designated in the recipe settings. An actual unit name may not be designated as data to be entered when a plurality of identical processing units are provided for one type of processing. Detailed processing requirements for each unit such as temperature and processing time (processing recipe) may be pre-stored in a memory 13a of the controller 13. Moreover, an operator can set further detailed requirements for step or unit designation.

Once the transfer recipe is entered in accordance with

the above procedure, a recipe flow, etc., is displayed on the main panel 2a. On correct recipe settings via the main panel 2a, the controller 13 automatically calculates the maximum processing time T_{max} that defines one processing
 5 cycle for each unit in a system-steady state.

Disclosed first is substrate processing in a transitional state in which a process performed by one unit does not affect a process performed by another unit.

Several wafers W are charged in each of the cassettes
 10 CR. The cassettes CR are set on the table 5 of the loading/unloading section 2 shown in FIGS. 1 to 3. After positioning of the cassettes CR, the wafers W are taken out by the sub-arm mechanism 6 and transferred into the loading/unloading section 2 one by one (step S1). Each of
 15 the transferred wafers W is transferred in the X-direction and transferred further into the processing section 3.

This wafer W is fed to the alignment unit ALIM of the processing section 3. After positioning for the wafer W by the unit ALIM, it is transferred to the adhesion unit AD via
 20 the main-arm mechanism 7.

A period of time from a moment at which the wafer W remains in the alignment unit ALIM to another moment at which it is fed to the adhesion unit AD is called a time t_1 . A timing chart for substrate processing in this transitional state
 25 is shown in FIG. 9. The extension unit EXT may be used instead of the alignment unit ALIM as the unit that firstly accepts the wafer W that has been transferred into the processing section 3.

The wafer W is subjected to hydrophobic processing in the adhesion unit AD (step S2). A period of time consumed by the unit AD for the hydrophobic processing is called a time t_2 .

The wafer W is taken out from the adhesion unit AD and fed to the cooling unit COL for cooling processing (step S3).
 35 A period of time consumed for the hydrophobic processing is called a time t_3 . The cooling processing can be performed by any one of the four identical cooling units COL1 to COL

4 (FIG. 4). This is the same for any processing described later. In other words, any of the identical processing units can perform a necessary processing when a plurality of identical units are installed. It is preferable to choose
 5 a processing unit from among the identical units to which a wafer W is transferred by the main-arm mechanism 7 for the shortest time.

Next, the wafer W is positioned so that it faces the resist-applying apparatus COT1 of the first processing-unit
 10 group G1 or the identical apparatus COT2 of the second group G2 (FIG. 4) and transferred therein by the main-arm mechanism 7. A resist is applied onto the wafer W while rotated for a processing time t4 (step S4).

The resist-applied wafer W is fed into the pre-baking
 15 unit PREBAKE so that it is dried out with evaporation of a solvent (thinner) from the resist (step S5). A period of time consumed for the pre-baking is called a time t5.

The wafer W taken out from the pre-baking unit PREBAKE is cooled by the cooling unit COL for a processing time t6
 20 (step S6), and then transferred to a second sub-arm mechanism 9 of the interface section 4 via the extension unit EXT.

The wafers W transferred to the second sub-arm mechanism 9 are charged in a buffer cassette BUCR (FIG. 1)
 25 one by one. The interface section 4 transfers each wafer W to the exposing apparatus 12 and receives the wafer W that has been subjected to exposure (step S7). The exposed wafer W is further subjected to exposure by a peripheral exposing apparatus WEE for exposing unnecessary resist applied on peripheral portions of the wafer W.

The further exposed wafer W is returned to the main-arm
 30 mechanism 7 in the manner reversal of the operation described above. The main-arm mechanism 7 transfers the wafer W into the post-exposure baking unit PREBAKE. A period of time from a moment at which the wafer W is taken out from the cooling
 35 unit COL to another moment at which it is fed into the post-exposure baking unit PREBAKE via exposing processing is called a time t7.

The wafer W is heated in the post-exposure baking unit PREBAKE for a processing time t8 (step S8) and then fed to the cooling unit COL, so that it is cooled to a predetermined temperature for a processing time t9 (step S9).

5 The cooled wafer W is fed into the resist-developing apparatus DEV of the first processing-unit group G1 or the second group G2 and developed for a processing time t10 (step S10).

10 The developed wafer W is fed to the post-baking unit POBAKE and heated so that it is dried out for a processing time t11 (step S11). The wafer W is further transferred to the cooling unit COL4 so that it is cooled for a processing time t12 (step S12) by the main-arm mechanism 7. The cooled wafer W is transferred to the loading/unloading section 2
15 via the extension unit EXT of the third processing-unit group G3 and charged in the cassette CR (step S13).

A pre-transfer time, a net processing time and a post-transfer time are defined in this transitional state as follows:

20 The pre-transfer time is a period from a moment at which a wafer W has been transferred to a unit for a certain processing to another moment at which the processing starts for the wafer W (a period from a moment at which a wafer W is taken out from a previous unit to another moment at which
25 the present unit starts processing).

The net processing time is a period consumed by any unit for processing a wafer W.

The post-transfer time is a period for which a processed wafer W is transferred again to the main-arm mechanism 7.

30 The net processing time is set as constant but depends on several requirements such as resist types. A waiting time added to each of the pre- and post-transfer time offers highly flexible processing. This transitional state, however, requires no waiting time because of no unnecessary
35 waiting-time consumption for the present wafer W to be processed against the previous wafer W under processing. Each of the processing time t1 to t13 is determined in

accordance with a given net processing time and the minimum transfer time.

A transfer time required for the main-arm mechanism 7 in this embodiment is about 5 sec. The post-transfer time is required for the main-arm mechanism 7 to take out a wafer W, and hence the shorter the post-waiting time that follows the post-transfer time, the better for stable process requirements (0 sec., being impossible though).

Transfer of wafers W from the cassettes CR one by one for respective processing in the transitional state will cause unnecessary waiting-time consumption for processing of a next wafer W against processing of the previous wafer W due to the fact that the previous wafer W delivered from a cassette CR is still under processing in a unit against the next wafer W that is to be fed into this unit.

The system 1 in this embodiment starts the maximum processing-time control when such unnecessary waiting-time consumption occurs.

For the time control, each processing unit is equipped with a sensor (not shown) for determining whether a wafer W is under processing. Each sensor is connected to the controller 13 to determine whether the unnecessary waiting-time consumption discussed above is occurring based on a detection signal from each sensor. When it is determined that the unnecessary waiting-time consumption is occurring, substrate-processing in the transitional state is halted and the processing in the steady state starts instead.

The steady state in this invention is a state that several wafers W have already been fed in the processing section 3 and the unnecessary waiting-time consumption discussed above is occurring over succeeding processing units.

The maximum processing-time control disclosed below is performed in this steady state.

In this control, each processing unit performs processing for the maximum processing time T_{max} , as one cycle, calculated by the controller 13 in recipe settings. The

maximum processing time T_{max} is defined as the maximum period among periods t_n/m consumed by each unit obtained by dividing a processing time " t_n " for each unit by the number of the identical units " m ". A period consumed by a processing unit equals to addition of the pre-transfer time, the net processing time and the post-transfer time.

Suppose that the developing apparatus DEV requires the longest processing time. When addition of the pre-transfer time, the net processing time and the post-transfer time gives a time t_{DEV} , the maximum processing time T_{max} is given as $t_{DEV}/2$ because the system 1 in this embodiment has two identical developing apparatus DEV.

The longest processing time per unit is defined as the maximum processing time T_{max} , and hence T_{max} is given as $t_{EXP}/1$ from $t_{EXP}/1 > t_{DEV}/2$ when only one exposing apparatus EXP is installed and addition of the pre-transfer time, the net time and the post-transfer time gives a time t_{EXP} .

Each unit performs processing for the maximum processing time T_{max} as obtained above as one cycle. Therefore, the requirement (pre-transfer time) + (net processing time) + (post-transfer time) $< T_{max}$ (1 cycle) is given to the processing units other than those requiring the maximum period consumed per unit. These units thus perform processing for (pre-transfer time) + (net processing time) + (post-transfer time) + (waiting time). One cycle may be determined as (maximum processing time) + (surplus time).

The following is disclosed with T_{max1} , T_{max2} , ..., and T_{max12} (= T_{max}) as one cycle for each unit for processing a wafer W that has been firstly transferred to the processing section 3, with reference to a timing chart shown in FIG. 10 in the steady state.

For the maximum processing time T_{max1} as the first cycle, the wafer W that has been firstly transferred to the processing section 3 is fed to the alignment unit ALIM of the third processing-unit group G3 for wafer positioning (step S1). Before this wafer W, in this steady state, several wafers W have already been under processing in respective

units of the processing section 3.

For the maximum processing time T_{max1} , T_{max1a} is defined as a pre-transfer time required for completion of wafer transfer to the alignment unit ALIM, T_{max1b} a net
 5 processing time for wafer alignment, and T_{max1c} a post-transfer time required for completion of wafer transfer from the alignment unit ALIM.

These time definition give $T_{max1a} + T_{max1b} + T_{max1c} < T_{max}$, which requires a waiting time within one cycle. In this
 10 embodiment, therefore, post-transfer is performed for the wafer W after waiting for a post-waiting time T_{max1d} in the alignment unit ALIM, that follows the net processing time T_{max1b} .

The same post-waiting time as for the alignment unit
 15 ALIM is set for all the processing units described below other than those requiring the maximum period consumed per unit.

The wafer W positioned as above is transferred to the adhesion unit AD by the main-arm mechanism 7, for hydrophobic processing (step S2). A period of time from a moment at which
 20 the wafer W is transferred to the adhesion unit AD for hydrophobic processing to another moment at which the wafer W is taken out from the adhesion unit AD is the maximum processing time T_{max2} . During the time T_{max2} , the next wafer W is transferred to the alignment unit ALIM for positioning
 25 (step S1).

Processing cycles are preferably set with a certain interval between each of successive wafers W. For example, a one-cycle starting time for a wafer W to be transferred to the processing section 3 is delayed by about 5 sec., from
 30 a one-cycle starting time for the previous wafer W.

Such interval for transfer time set for the main-arm mechanism 7 among the processing units avoids interference which may otherwise occur in transfer of several wafers W by the main-arm mechanism 7 to the processing units. For
 35 example, in this embodiment, a wafer W is transferred from the adhesion unit AD to the cooling unit COL by the main-arm mechanism 7 for 5 sec., and after that, the next wafer W is

transferred from the alignment unit ALIM to the adhesion unit AD for 5 sec.

5 The wafer W for which hydrophobic processing has been completed for the time Tmax2 is subjected to cooling processing in the cooling unit COL (step S3) for the time Tmax3. The cooling processing can be performed by any unit among the four identical cooling units COL1 to COL4. The cooling unit must, however, be selected from among the units COL1 to COL4 so that a wafer W will not interfere with the
10 previous wafer W that is under the processing in the selected unit.

The unit selection from among identical processing units is performed by the controller 13 based on a signal output by a sensor (not shown) attached to each unit. This
15 sensor determines whether each identical unit is performing processing or wafer transferring, or there is a wafer W in it or not. The sensor output may be displayed on the main panel 2a.

Also in the following processing, any unit among the
20 identical units for the same processing is selected so that a wafer W will not interfere with the previous wafer W that is under the processing in the selected unit.

During the time Tmax3, a wafer W (one-wafer behind) that has been transferred to the processing section 3 just after
25 the wafer W now under the cooling processing is subjected to hydrophobic processing in the adhesion unit AD (step S2), and another wafer W (two-wafer behind) just after the wafer W now under the hydrophobic processing is transferred to the alignment unit ALIM and subjected to positioning.

30 The wafer W for which the cooling processing has been completed is transferred to the resist-applying apparatus COT in which a resist is applied onto the wafer W while being rotated for the processing time Tmax4 (step S4). During the time Tmax4, a wafer W (one-wafer behind) that has transferred
35 to the processing section 3 is subjected to cooling processing in the cooling unit COL, another transferred wafer W (two-wafer behind) is subjected to hydrophobic processing

in the adhesion unit AD (step S2), and still another transferred wafer W (three-wafer behind) is subjected to positioning in the alignment unit ALIM (step S1).

Also within the succeeding processing times Tmax5 to Tmax11, wafers W are subjected to respective processing one by one in the corresponding units, which is not disclosed though.

The wafer W on which resist has been applied within the processing time Tmax4 is transferred to the pre-baking unit PREBAKE at the start of the next processing time Tmax5.

FIGS. 8A and 8B show vertical sections of an example of the pre-baking unit PREBAKE or other thermal processing units.

A thermal processing unit 101 has a block 102 opened upwards. Installed in the block 102 is a hot plate 103 on which a wafer W is placed and heated. The hot plate 103 is provided with several (for example, three) lift pins 104 for supporting the wafer W during wafer transfer into and from the thermal processing unit 101. The lower ends of the lift pins 104 are connected to an elevation drive mechanism (not shown) via a pin-supporting member 105 so that they can be elevated through the hot plate 103.

An upper cover 106 is provided over the hot plate 103 with a space S therebetween for wafer transfer. An exhaust pipe 107 is connected to the upper cover 106, for exhausting gas that will be generated during thermal processing.

Installed further in the block 102 is a cylinder shutter 108 that covers the space S and the hot plate 103. The shutter 108 is also elevated by an elevation drive mechanism (not shown).

A wafer W is taken into the thermal processing unit 101 while it is lifted up from the hot plate 103 by the lift pins 101 during which the shutter 108 is elevated so that the space S is closed. The wafer W remains an up-lifted position while waiting for the pre-baking processing.

In thermal processing by the pre-baking unit PREBAKE, the wafer W is taken into the unit for a pre-transfer (before

processing) time Tmax5a and waits for a pre-waiting (before processing) time Tmax5b while it is lifted up.

Then, as shown in FIG. 8B, the wafer W is lifted down on the hot plate 103 while the lift pins 104 are moved down, for pre-baking for a net processing time Tmax5c (step S5) and taken out from the pre-baking unit PREBAKE for a post-transfer (after processing) time Tmax5d.

The total of the pre-transfer time, the pre-waiting time, the net processing time and the post-transfer time equals to the processing time Tmax5 ($= \text{Tmax5a} + \text{Tmax5b} + \text{Tmax5c} + \text{Tmax5d}$).

The wafer W is then subjected to cooling processing in the cooling unit COL for a processing time Tmax6 (step S6) and then transferred into the exposing unit EXP for exposure to a given pattern for a processing time Tmax7 (step S7), with peripheral exposure by the peripheral exposing apparatus WEE.

The wafer W for which the exposing processing has been completed is transferred to the post-exposure baking unit PEBAKE within a pre-transfer time Tmax8a while it is lifted up from the hot plate 103 by the lift pins 101, as shown in FIG. 8A.

After being lifted up for a pre-waiting time Tmax8b, the wafer W is lifted down on the hot plate 103 while the lift pins 104 are moved down, for post-exposure baking PREBAKE for a net processing time Tmax8c (step S8). The wafer W is then taken out from the post-exposure baking unit PREBAKE within Tmax8d.

The total of the pre-transfer time, the pre-waiting time, the net processing time and the post-transfer time equals to the processing time Tmax8 ($= \text{Tmax8a} + \text{Tmax8b} + \text{Tmax8c} + \text{Tmax8d}$).

The wafer W for which the thermal processing has been completed is transferred to the cooling unit COL for cooling processing for a processing time Tmax9 (step S9). Then, the wafer W is taken out from the cooling unit COL and transferred to the resist-developing apparatus DEV for developing

processing for a processing time $T_{\max 10}$ (step S10). The wafer W is further transferred to the post-baking unit POBAKE for thermal and dry processing by a given cycle time $T_{\max 11}$. Like the other thermal processing units, a pre-waiting time

5 $T_{\max 11b}$ is set for the post-baking unit POBAKE.

The wafer W is then transferred to the cooling unit COL by the main-arm mechanism 7, for cooling processing for a processing time $T_{\max 12}$ (step S12), and returned to the cassette CR (step S13).

10 As disclosed, a wafer W is taken into and out from the processing section 3 for a period from $T_{\max 1}$ to $T_{\max 12}$ in the steady state.

Accordingly, the present invention performs wafer processing in the steady state so that each unit performs

15 respective processing for the maximum processing time T_{\max} decided in accordance with the wafer-processing recipe with a pre-waiting time set at the start of the maximum processing time in each thermal processing while each wafer W is lifted up, thus drastically decreasing thermal effects.

20 Second Embodiment

This embodiment relates to pre-waiting time settings to two processing units against one unit by which unnecessary waiting-time consumption occurs. The processing in the transitional state is the same as that for the first

25 embodiment and hence not disclosed here.

The substrate processing system in this embodiment is identical to the one for the first embodiment shown in FIGS. 1 to 3. The flowchart shown in FIG. 6 for the first embodiment is also used in this embodiment.

30 The difference between the first and the second embodiments is waiting timing for each processing. FIG. 11 is a timing chart for the substrate-processing timing in this embodiment. The timing chart shown in FIG. 9 for the first embodiment includes pre-waiting time adjustment within one

35 maximum processing time for one processing unit by which unnecessary waiting-time consumption occurs. On the other hand, this embodiment includes pre-waiting time adjustment

within a processing time over two processing units against one unit by which unnecessary waiting-time consumption occurs.

Disclosed below is pre-waiting time setting before
5 development processing DEV.

The maximum processing time T_{max} is calculated like the first embodiment. Each unit performs processing per maximum processing time in the first embodiment. Like the first embodiment, the second embodiment could suffer from
10 unnecessary waiting-time consumption for processing followed by long processing for each unit. Such unnecessary waiting-time consumption will cause change in pattern width, etc. In order to solve such a problem, the second embodiment adjusts the maximum processing time corresponding to a
15 two-cycle time so that a net processing time T_{maxb} for each thermal processing requires the least waiting time before a net processing time for development.

The maximum processing time T_{max8} given to the post-exposure baking PREBAKING consists of a pre-transfer
20 time T_{max8a} , a net processing time T_{max8b} , a post-transfer time T_{max8c} and a waiting time T_{max8d} .

The maximum processing time T_{max9} given to the cooling unit COL consists of a pre-transfer time T_{max9a} , a net
25 processing time T_{max9b} , a post-transfer time T_{max9c} and a waiting time T_{max9d} . The pre-transfer time T_{maxa} and the post-transfer time T_{maxb} require a certain least period.

Therefore, in this embodiment, the waiting time T_{max8d} for the post-exposure baking unit PREBAKING is set before the net processing and the waiting time T_{max9d} for the cooling
30 unit COL is set at zero. The settings offer the least waiting time after the net post-exposure baking processing PREBAKING but before the net development processing.

Accordingly, wafers W can be transferred to the development processing for the minimum time in this
35 embodiment while the least transfer time is required though. This embodiment thus advantageous than the first embodiment in which development processing is performed after the elapse

of waiting time occurred at the cooling unit COL due to allocation of one-cycle time to each processing unit.

A waiting time for each of the pre-baking PREBAKE and the cooling COL before exposure EXP is also adjusted in the same way as disclosed above.

As disclosed, this embodiment achieves short waiting time after thermal processing, compared to that in the first embodiment, thus providing a substrate-processing system that hardly suffers from thermal effects.

Disclosed in this embodiment is the waiting-time adjustment for two processing units before development DEV or pre-baking PREBAKE. However, if the adjustment for two processing units cannot produce the least waiting time, it is also possible to make waiting-time adjustment within 3 x or 4 x one-cycle time to shorten the waiting time after thermal processing.

A waiting-time adjustment is, for example, required for three processing units before development when $T_{\max 8a} - \min + T_{\max 8c} - \min + T_{\max 9a} - \min + T_{\max 9c} - \min < T_{\max 10b}$.

Accordingly, this embodiment achieves flexible waiting-time adjustments in accordance with the ratio of net processing time $T_{\max b}$ to maximum processing time.

Third Embodiment

This embodiment relates to allocation of processing time to two processing units within a one-cycle time. The processing in the transitional state and the system structure in this embodiment are identical to those for the first embodiment and hence not disclosed here.

The substrate processing system in this embodiment is identical to the one for the first embodiment shown in FIGS. 1 to 3. The flow chart shown in FIG. 6 for the first embodiment is also used in this embodiment.

The difference between the first and the third embodiments lies in the timing chart for each processing. FIG. 12 is a timing chart for the substrate-processing in this embodiment.

In this embodiment, the processing in an adhesion unit

AD and a cooling unit COL is performed for the maximum processing time $T_{\max 2a}$ (one-cycle time).

Likewise, a one-cycle time is given to a pre-baking unit PREBAKE and a cooling unit COL, a post-exposure baking unit POBAKE and a cooling unit COL, and post-exposure baking unit POBAKE and a cooling unit COL.

A processing time for the cooling unit is relatively short in this substrate-processing system. It is thus expected that the addition of a processing time for thermal processing and that for cooling processing is shorter than that for exposing processing per exposing apparatus EXP or developing processing per developing apparatus DEV. Allocation of a one-cycle time to each of the thermal processing unit and the cooling unit in this case will result in a long waiting time compared to a net processing time.

Accordingly, a one-cycle time is given to these two processing units in this embodiment for avoiding such improper settings.

For example, for the pre-baking unit PREBAKE and the cooling unit COL, a one-cycle time is set in the order of a pre-transfer time $T_{\max 6a-1}$ to the pre-baking unit PREBAKE, a pre-waiting time $T_{\max 6d}$, a net processing time $T_{\max 6b-1}$ for pre-baking, a post-transfer time $T_{\max 6c-1}$ from the pre-baking unit PREBAKE, a pre-transfer time $T_{\max 6a-2}$ to the cooling unit COL, a net processing time $T_{\max 6b-2}$ for cooling, a post-transfer time $T_{\max 6c-2}$ from the cooling unit COL.

Waiting time $T_{\max 2d}$, $T_{\max 4d}$ and $T_{\max 8d}$ are also set for other processing units in the same way.

Allocation of a one-cycle time to two processing units as disclosed decreases the total number of cycles for enhanced throughput.

This cycle allocation can be applied even if a processing time for two units is longer than the maximum processing time for each of other units, with setting the processing time for the two units as the maximum processing time. Moreover, a one-cycle time may be allocated to three or more processing units.

Fourth Embodiment

The first embodiment includes the cycle-time settings based on a period for a wafer W to remain in each processing unit.

5 In this embodiment, on the other hand, includes cycle-time settings for a temporal cycle time (called wafer remaining-induced unnecessary waiting-time-consumption cycle time hereinafter) that is set based on a period for a wafer W to remain in each processing unit or another temporal
10 cycle time (called transfer-induced unnecessary waiting-time-consumption cycle time hereinafter) that is set based on a period for a wafer W to be transferred by an arm.

The system structure in this embodiment is identical to that for the first embodiment and hence not disclosed here.

15 Calculation of the transfer-induced unnecessary waiting-time-consumption cycle time (transfer-induced rate controlling cycle time) is disclosed.

Parameters required for calculation of the transfer-induced unnecessary waiting-time-consumption
20 cycle time are set as follows:

Set at first is a one-cycle time (called a time "cra" hereinafter) for the first sub-arm mechanism 6 from a moment at which it takes out a wafer W from a cassette CR in the loading/unloading section 2, via transferring the wafer W
25 to a processing unit of the processing section 3, that firstly receives the wafer W, such as, the alignment unit ALIM or the extension unit EXT, to another moment at which it takes out the next wafer W. The time "cra" is set, for example, at 20 sec., for the same type of substrate-processing system,
30 however, depends on system types.

Set secondary is a main-arm cycle-round time (called a time "pra" hereinafter) that is the total of periods required for the main-arm 8 to transfer a wafer W from a processing unit to another unit for one cycle in the
35 processing section 3. A period required for the main-arm 8 to transfer a wafer W from a one unit to another for one cycle depends on each unit. The time "pra" thus equals to a period

required per unit for the main-arm 8 for one cycle.

Set thirdly is a period in one cycle (called a time "ira" hereinafter) required for wafer transfer between the processing section 3 and the exposing apparatus 12. The time "ira" is obtained by multiplying a transfer time "ts" by the number of steps "p". The transfer time "ts" is obtained per wafer W by adding a period for which a wafer W is transferred from the processing section 3 to the exposing apparatus 12 and another period for which the wafer W is taken out from the exposing apparatus 12. The number "p" is the number of steps for wafer transfer and receiving within one cycle. The time "ira" is obtained, for example, as $7.5 \text{ sec} \times p$ when the transfer time "ts" is 7.5 sec.

The maximum time among the three parameters time "cra", time "pra" and time "ira" calculated as above is set as the transfer-induced unnecessary waiting-time-consumption cycle time.

Calculation of the wafer remaining-induced unnecessary waiting-time-consumption cycle time (wafer remaining-induced rate controlling cycle time) is not disclosed here because it is understood from the first to the third embodiments.

Either the wafer remaining-induced unnecessary waiting-time-consumption cycle time or the transfer-induced unnecessary waiting-time-consumption cycle time, larger than the other, is set as the temporal cycle time.

It is determined next as disclosed below whether the temporal cycle time can be used as a legitimate cycle time. In this embodiment, any cycle time other than the legitimate cycle time is a provisional cycle time for decision of cycle time. Several types of processing are sequentially performed per legitimate cycle time.

Calculated first is a period (called an ira-transfer time hereinafter) for which a wafer W is transferred to a processing unit (called a starter unit hereinafter) that performs processing just before the wafer W is transferred to the exposing apparatus 12.

The starter unit is a CPL unit that is capable of wafer transfer to the exposing apparatus 12 and also wafer processing such as cooling.

5 The ira-transfer time is the total of arm wafer -
transferring periods among the processing units until wafer transfer to the exposing apparatus 12 is completed in one cycle. For processing units capable of simultaneous wafer transfer and reception, it is preferable to add values each obtained by dividing a transfer time by 2 because a transfer
10 time required for such unit is just a half of the transfer time.

Calculated next is a period (called an ira-processing time) required for processing in the starter unit. The temporal cycle time is subtracted from the ira-transfer time
15 and the ira-processing time to obtain an ira-delay time as follows:

$$(\text{ira-delay time}) = \{(\text{ira-transfer time}) + (\text{ira-processing time})\} - (\text{temporal cycle time})$$

The ira-delay time indicates a period for which the
20 starter unit performs processing beyond the temporal cycle time. Without cycle-time settings so that no ira-delay time is produced, unnecessary waiting-time consumption will occur due to processing in the starter unit even though the other units in the processing section 3 perform processing within
25 the cycle time.

In order to avoid such occurrence of unnecessary waiting-time consumption, it is determined whether the addition of the time "ira" and the ira-delay time is longer than the temporal cycle time. The addition longer than the
30 temporal cycle time will cause unnecessary waiting-time consumption due to processing in the starter unit to the other units.

It is thus determined that processing in the starter unit will cause unnecessary waiting-time consumption to all
35 processing in processing units including the units in the processing section 3 when $(\text{time "ira"} + (\text{ira-delay time}) > (\text{temporal cycle time}))$. And then $(\text{time "ira"} + (\text{ira-delay$

time) is decided as the legitimate cycle time.

On the other hand, when (time "ira") + (ira-delay time) < (temporal cycle time), it is determined that processing in the starter unit will not cause unnecessary waiting-time consumption to the other processing units. The temporal cycle time is thus decided as the legitimate cycle time.

As disclosed, this embodiment achieves flexible cycle-time settings under consideration of unnecessary waiting-time consumption due to processing in each unit and also to transfer processing.

This embodiment uses a processing unit as the starter unit, from which a wafer W is transferred to the exposing apparatus 12.

Not only that, however, any other units such as the extension unit EXT of the processing section 3 can be used as the starter unit for decision of cycle time in the same way as described above.

For example, the time "ira", the ira-delay time and the ira-processing time are calculated for decision of cycle time in the same way as described above with the extension units EXT as the starter units, that are installed in the third to the fifth processing-unit groups G3 to G5 of the processing section 3 and when the extension units EXT are capable of processing such as cooling and also wafer transfer-in and -out.

The legitimate cycle time disclosed above is calculated for example by the controller 13. Then, based on the legitimate cycle time, the controller 13 calculates the pre-transfer time, the post-transfer time, and so on, for the processing units of the loading/unloading section 2, the processing section 3, the interface section 4 and the exposing section 12.

The pre-transfer time and the post-transfer time can be calculated like the first embodiment such as shown in FIG. 10. The pre- and the post-transfer times calculated per processing unit are stored in a database (not shown) and sent to a control mechanism (not shown) connected to the units.

The control mechanism drives the processing units at the timing decided in accordance with the pre- and the post-transfer times.

5 The present invention is not limited to the embodiments disclosed above. In other words, the substrate-processing system according to the present invention can be applied to any processing units other than the substrate-processing units described above.

10 Various types of processing units can be installed in each processing-unit group. The number of processing units is also flexible.

The present invention is applied to the substrate processing system used for photolithography in the foregoing embodiments. This invention is, however, also applicable
15 to a processing system such as shown in FIG. 13.

Elements in the system shown in FIG. 13 that are the same as or analogous to elements in the system shown in FIG. 1 are referenced by the same reference numbers and will not be explained in detail.

20 The processing system shown in FIG. 13 has the loading/unloading section 2 and the processing section 3, without the interface section 4 and the exposing apparatus 12. Moreover, the processing units installed in the first and the second processing-unit groups G1 and G2 of the
25 processing section 3 are any processing solution-used units other than the resist-applying units COT and the resist-developing units DEV.

It is further understood by those skilled in the art that various change and modification may be made in the
30 invention without departing from the spirit and scope thereof.

Moreover, the foregoing embodiments are disclosed on pre-waiting (before processing) while a wafer W is lifted up in each thermal processing unit. Not only, that, however,
35 the present invention can be applied to pre-waiting in which a wafer W is once remained in an empty unit such as an extension unit EXT before it is transferred a thermal processing unit.

As disclosed above, according to the present invention, one cycle is set based on the longest processing time among processing units and also a pre-waiting time is set within the set one cycle, thus drastically decreasing unnecessary
 5 waiting-time consumption discussed above.

1001
 1002
 1003
 1004
 1005
 1006
 1007
 1008
 1009
 1010
 1011
 1012
 1013
 1014
 1015
 1016
 1017
 1018
 1019
 1020
 1021
 1022
 1023
 1024
 1025
 1026
 1027
 1028
 1029
 1030
 1031
 1032
 1033
 1034
 1035
 1036
 1037
 1038
 1039
 1040
 1041
 1042
 1043
 1044
 1045
 1046
 1047
 1048
 1049
 1050
 1051
 1052
 1053
 1054
 1055
 1056
 1057
 1058
 1059
 1060
 1061
 1062
 1063
 1064
 1065
 1066
 1067
 1068
 1069
 1070
 1071
 1072
 1073
 1074
 1075
 1076
 1077
 1078
 1079
 1080
 1081
 1082
 1083
 1084
 1085
 1086
 1087
 1088
 1089
 1090
 1091
 1092
 1093
 1094
 1095
 1096
 1097
 1098
 1099
 1100
 1101
 1102
 1103
 1104
 1105
 1106
 1107
 1108
 1109
 1110
 1111
 1112
 1113
 1114
 1115
 1116
 1117
 1118
 1119
 1120
 1121
 1122
 1123
 1124
 1125
 1126
 1127
 1128
 1129
 1130
 1131
 1132
 1133
 1134
 1135
 1136
 1137
 1138
 1139
 1140
 1141
 1142
 1143
 1144
 1145
 1146
 1147
 1148
 1149
 1150
 1151
 1152
 1153
 1154
 1155
 1156
 1157
 1158
 1159
 1160
 1161
 1162
 1163
 1164
 1165
 1166
 1167
 1168
 1169
 1170
 1171
 1172
 1173
 1174
 1175
 1176
 1177
 1178
 1179
 1180
 1181
 1182
 1183
 1184
 1185
 1186
 1187
 1188
 1189
 1190
 1191
 1192
 1193
 1194
 1195
 1196
 1197
 1198
 1199
 1200
 1201
 1202
 1203
 1204
 1205
 1206
 1207
 1208
 1209
 1210
 1211
 1212
 1213
 1214
 1215
 1216
 1217
 1218
 1219
 1220
 1221
 1222
 1223
 1224
 1225
 1226
 1227
 1228
 1229
 1230
 1231
 1232
 1233
 1234
 1235
 1236
 1237
 1238
 1239
 1240
 1241
 1242
 1243
 1244
 1245
 1246
 1247
 1248
 1249
 1250
 1251
 1252
 1253
 1254
 1255
 1256
 1257
 1258
 1259
 1260
 1261
 1262
 1263
 1264
 1265
 1266
 1267
 1268
 1269
 1270
 1271
 1272
 1273
 1274
 1275
 1276
 1277
 1278
 1279
 1280
 1281
 1282
 1283
 1284
 1285
 1286
 1287
 1288
 1289
 1290
 1291
 1292
 1293
 1294
 1295
 1296
 1297
 1298
 1299
 1300
 1301
 1302
 1303
 1304
 1305
 1306
 1307
 1308
 1309
 1310
 1311
 1312
 1313
 1314
 1315
 1316
 1317
 1318
 1319
 1320
 1321
 1322
 1323
 1324
 1325
 1326
 1327
 1328
 1329
 1330
 1331
 1332
 1333
 1334
 1335
 1336
 1337
 1338
 1339
 1340
 1341
 1342
 1343
 1344
 1345
 1346
 1347
 1348
 1349
 1350
 1351
 1352
 1353
 1354
 1355
 1356
 1357
 1358
 1359
 1360
 1361
 1362
 1363
 1364
 1365
 1366
 1367
 1368
 1369
 1370
 1371
 1372
 1373
 1374
 1375
 1376
 1377
 1378
 1379
 1380
 1381
 1382
 1383
 1384
 1385
 1386
 1387
 1388
 1389
 1390
 1391
 1392
 1393
 1394
 1395
 1396
 1397
 1398
 1399
 1400
 1401
 1402
 1403
 1404
 1405
 1406
 1407
 1408
 1409
 1410
 1411
 1412
 1413
 1414
 1415
 1416
 1417
 1418
 1419
 1420
 1421
 1422
 1423
 1424
 1425
 1426
 1427
 1428
 1429
 1430
 1431
 1432
 1433
 1434
 1435
 1436
 1437
 1438
 1439
 1440
 1441
 1442
 1443
 1444
 1445
 1446
 1447
 1448
 1449
 1450
 1451
 1452
 1453
 1454
 1455
 1456
 1457
 1458
 1459
 1460
 1461
 1462
 1463
 1464
 1465
 1466
 1467
 1468
 1469
 1470
 1471
 1472
 1473
 1474
 1475
 1476
 1477
 1478
 1479
 1480
 1481
 1482
 1483
 1484
 1485
 1486
 1487
 1488
 1489
 1490
 1491
 1492
 1493
 1494
 1495
 1496
 1497
 1498
 1499
 1500
 1501
 1502
 1503
 1504
 1505
 1506
 1507
 1508
 1509
 1510
 1511
 1512
 1513
 1514
 1515
 1516
 1517
 1518
 1519
 1520
 1521
 1522
 1523
 1524
 1525
 1526
 1527
 1528
 1529
 1530
 1531
 1532
 1533
 1534
 1535
 1536
 1537
 1538
 1539
 1540
 1541
 1542
 1543
 1544
 1545
 1546
 1547
 1548
 1549
 1550
 1551
 1552
 1553
 1554
 1555
 1556
 1557
 1558
 1559
 1560
 1561
 1562
 1563
 1564
 1565
 1566
 1567
 1568
 1569
 1570
 1571
 1572
 1573
 1574
 1575
 1576
 1577
 1578
 1579
 1580
 1581
 1582
 1583
 1584
 1585
 1586
 1587
 1588
 1589
 1590
 1591
 1592
 1593
 1594
 1595
 1596
 1597
 1598
 1599
 1600
 1601
 1602
 1603
 1604
 1605
 1606
 1607
 1608
 1609
 1610
 1611
 1612
 1613
 1614
 1615
 1616
 1617
 1618
 1619
 1620
 1621
 1622
 1623
 1624
 1625
 1626
 1627
 1628
 1629
 1630
 1631
 1632
 1633
 1634
 1635
 1636
 1637
 1638
 1639
 1640
 1641
 1642
 1643
 1644
 1645
 1646
 1647
 1648
 1649
 1650
 1651
 1652
 1653
 1654
 1655
 1656
 1657
 1658
 1659
 1660
 1661
 1662
 1663
 1664
 1665
 1666
 1667
 1668
 1669
 1670
 1671
 1672
 1673
 1674
 1675
 1676
 1677
 1678
 1679
 1680
 1681
 1682
 1683
 1684
 1685
 1686
 1687
 1688
 1689
 1690
 1691
 1692
 1693
 1694
 1695
 1696
 1697
 1698
 1699
 1700
 1701
 1702
 1703
 1704
 1705
 1706
 1707
 1708
 1709
 1710
 1711
 1712
 1713
 1714
 1715
 1716
 1717
 1718
 1719
 1720
 1721
 1722
 1723
 1724
 1725
 1726
 1727
 1728
 1729
 1730
 1731
 1732
 1733
 1734
 1735
 1736
 1737
 1738
 1739
 1740
 1741
 1742
 1743
 1744
 1745
 1746
 1747
 1748
 1749
 1750
 1751
 1752
 1753
 1754
 1755
 1756
 1757
 1758
 1759
 1760
 1761
 1762
 1763
 1764
 1765
 1766
 1767
 1768
 1769
 1770
 1771
 1772
 1773
 1774
 1775
 1776
 1777
 1778
 1779
 1780
 1781
 1782
 1783
 1784
 1785
 1786
 1787
 1788
 1789
 1790
 1791
 1792
 1793
 1794
 1795
 1796
 1797
 1798
 1799
 1800
 1801
 1802
 1803
 1804
 1805
 1806
 1807
 1808
 1809
 1810
 1811
 1812
 1813
 1814
 1815
 1816
 1817
 1818
 1819
 1820
 1821
 1822
 1823
 1824
 1825
 1826
 1827
 1828
 1829
 1830
 1831
 1832
 1833
 1834
 1835
 1836
 1837
 1838
 1839
 1840
 1841
 1842
 1843
 1844
 1845
 1846
 1847
 1848
 1849
 1850
 1851
 1852
 1853
 1854
 1855
 1856
 1857
 1858
 1859
 1860
 1861
 1862
 1863
 1864
 1865
 1866
 1867
 1868
 1869
 1870
 1871
 1872
 1873
 1874
 1875
 1876
 1877
 1878
 1879
 1880
 1881
 1882
 1883
 1884
 1885
 1886
 1887
 1888
 1889
 1890
 1891
 1892
 1893
 1894
 1895
 1896
 1897
 1898
 1899
 1900
 1901
 1902
 1903
 1904
 1905
 1906
 1907
 1908
 1909
 1910
 1911
 1912
 1913
 1914
 1915
 1916
 1917
 1918
 1919
 1920
 1921
 1922
 1923
 1924
 1925
 1926
 1927
 1928
 1929
 1930
 1931
 1932
 1933
 1934
 1935
 1936
 1937
 1938
 1939
 1940
 1941
 1942
 1943
 1944
 1945
 1946
 1947
 1948
 1949
 1950
 1951
 1952
 1953
 1954
 1955
 1956
 1957
 1958
 1959
 1960
 1961
 1962
 1963
 1964
 1965
 1966
 1967
 1968
 1969
 1970
 1971
 1972
 1973
 1974
 1975
 1976
 1977
 1978
 1979
 1980
 1981
 1982
 1983
 1984
 1985
 1986
 1987
 1988
 1989
 1990
 1991
 1992
 1993
 1994
 1995
 1996
 1997
 1998
 1999
 2000
 2001
 2002
 2003
 2004
 2005
 2006
 2007
 2008
 2009
 2010
 2011
 2012
 2013
 2014
 2015
 2016
 2017
 2018
 2019
 2020
 2021
 2022
 2023
 2024
 2025
 2026
 2027
 2028
 2029
 2030
 2031
 2032
 2033
 2034
 2035
 2036
 2037
 2038
 2039
 2040
 2041
 2042
 2043
 2044
 2045
 2046
 2047
 2048
 2049
 2050
 2051
 2052
 2053
 2054
 2055
 2056
 2057
 2058
 2059
 2060
 2061
 2062
 2063
 2064
 2065
 2066
 2067
 2068
 2069
 2070
 2071
 2072
 2073
 2074
 2075
 2076
 2077
 2078
 2079
 2080
 2081
 2082
 2083
 2084
 2085
 2086
 2087
 2088
 2089
 2090
 2091
 2092
 2093
 2094
 2095
 2096
 2097
 2098
 2099
 2100
 2101
 2102
 2103
 2104
 2105
 2106
 2107
 2108
 2109
 2110
 2111
 2112
 2113
 2114
 2115
 2116
 2117
 2118
 2119
 2120
 2121
 2122
 2123
 2124
 2125
 2126
 2127
 2128
 2129
 2130
 2131
 2132
 2133
 2134
 2135
 2136
 2137
 2138
 2139
 2140
 2141
 2142
 2143
 2144
 2145
 2146
 2147
 2148
 2149
 2150
 2151
 2152
 2153
 2154
 2155
 2156
 2157
 2158
 2159
 2160
 2161
 2162
 2163
 2164
 2165
 2166
 2167
 2168
 2169
 2170
 2171
 2172
 2173
 2174
 2175
 2176
 2177
 2178
 2179
 2180
 2181
 2182
 2183
 2184
 2185
 2186
 2187
 2188
 2189
 2190
 2191
 2192
 2193
 2194
 2195
 2196
 2197
 2198
 2199
 2200
 2201
 2202
 2203
 2204
 2205
 2206
 2207
 2208
 2209
 2210
 2211
 2212
 2213
 2214
 2215
 2216
 2217
 2218
 2219
 2220
 2221
 2222
 2223
 2224
 2225
 2226
 2227
 2228
 2229
 2230
 2231
 2232
 2233
 2234
 2235
 2236
 2237
 2238
 2239
 2240
 2241
 2242
 2243
 2244
 2245
 2246
 2247
 2248
 2249
 2250
 2251
 2252
 2253
 2254
 2255
 2256
 2257
 2258
 2259
 2260
 2261
 2262
 2263
 2264
 2265
 2266
 2267
 2268
 2269
 2270
 2271
 2272
 2273
 2274
 2275
 2276
 2277
 2278
 2279
 2280
 2281
 2282
 2283
 2284
 2285
 2286
 2287
 2288
 2289
 2290
 2291
 2292
 2293
 2294
 2295
 2296
 2297
 2298
 2299
 2300
 2301
 2302
 2303
 2304
 2305
 2306
 2307
 2308
 2309
 2310
 2311
 2312
 2313
 2314
 2315
 2316
 2317
 2318
 2319
 2320
 2321
 2322
 2323
 2324
 2325
 2326
 2327
 2328
 2329
 2330
 2331
 2332
 2333
 2334
 2335
 2336
 2337
 2338
 2339
 2340
 2341
 2342
 2343
 2344
 2345
 2346
 2347
 2348
 2349
 2350
 2351
 2352
 2353
 2354
 2355
 2356
 2357
 2358
 2359
 2360